


MB840M2P-B



MB842MP-B



CE Cremax Europe GmbH
 Weidenweg 21H
 47059 Duisburg, Germany
 Email: support@icydock.com

Copyright © ICY DOCK International. All Rights Reserved. 650292 VER 1.0

1 Package Contents • Packungsinhalt • Contenu • Contenido del paquete
 • 包装について • 包装説明 • 包装说明

(MB840M2P-B)	(MB842MP-B)	(MB840M2P-B)	(MB842MP-B)
Device		Thermal Pad × 2	Thermal Pad × 4

(MB840M2P-B)		
Full / Half Height Expansion Slot Faceplate	User Manual	1 x #6-32*5 Hexagon Phillips Screw with Washer for Device

① Note : Please use the included screw to secure the device.

2 Device Information • Geräteinformationen • Informations dispositifif
 • Información del dispositivo • 本体説明 • 機體説明 • 机体说明

MB840M2P-B
 ▼ Top View

- ① Half Height IO Faceplate
- ② Full Height IO Faceplate
- ③ 2 Pin Header for Front Panel LED Activity Indicator
- ④ PCIe 4.0 x4 Golden Finger (Compatible with PCIe x4 / x8 / x16 Slot)

- ✓ x4
- ✓ x8
- ✓ x16

▼ Front View

- ① Drive Tray Ejection Button
- ② LED Indicator (Power : Solid Green ; Drive Access: Flashing Green)

MB842MP-B
 ▼ Top View

- ① PCIe 4.0 x8 Connector (Compatible with PCIe x8 and x16 Slot)
- ② 2 Pin LED Signal Output for Drive Activity)

- ✓ x8
- ✓ x16

▼ Front View

- ① Drive Tray Ejection Button
- ② Full Height PCIe Bracket
- ③ LED Indicator (Power : Solid Green LED ; Drive Access : Flashing Green LED)

① Note : Please make sure your motherboard supports "PCIe bifurcation" to use dual M.2 NVMe SSDs simultaneously. Check the user manual of the motherboard or contact the motherboard manufacturer for this info. The motherboard will only detect single M.2 NVMe SSD without PCIe bifurcation feature.

PCIe Bifurcation Setting

1. Make sure your motherboard supports the PCIe bifurcation feature.
2. Enter the BIOS menu.
3. Select EZ/Easy and then click Advance/Classic Mode
4. Locate PCIe port configuration and then change the setting to x4 x4 or x4 x4 x4 x4

MB840M2P-B & MB842MP-B
 ▼ Drive Tray Inner View

- ① Adjustable M.2 SSD Locker
- ② Error-proofing Pin to Align M.2 Connector

3 Installation Guide • Installationsanleitung • Guide d'Installation • Guía de instalación • 製品の組み込み手順について • 操作步驟 • 操作步驟

3-1

Push the drive tray ejection button to eject the drive tray.

3-2

Pull to remove the drive tray.

3-3

Press down the rear of the top cover and push towards the guided arrow to open the top cover.

3-4

Remove the clear protective film on both sides of the 1mm or 0.7mm thermal pad (depends on your SSD thickness) and then paste it on the tray plate.

(Optional)

If there is a significant height difference between the components on the M.2 SSD, cut the unused thermal pad into small pieces, and paste them onto the lower components to make complete contact with the thermal pad that you paste on the tray plate for best heat transfer.

Warning
 If using the 1mm thermal pad causes difficulties to insert the M.2 drive tray into the enclosure, replace the 1mm thermal pad with the 0.7mm thermal pad.

3-5

Secure the drive with adjustable M.2 SSD locker.

3-6

Secure the drive with adjustable M.2 SSD locker.

3-7

Connect the 2 pin header to the system's LED light signal cable for frontal drive activity light.

3-8 (MB840M2P-B)

(MB842MP-B)

4 Device Installation • Installation eines Gerätes • Installation du dispositif
 • Instalación del dispositivo de • デバイス取付手順 • 装置安裝步驟
 • 设备安装步驟

MB840M2P-B **MB842MP-B**

- ① Use the included #6-32*5 screw to secure the device.
- ② Fully connect the device's PCIe connector into the system's PCIe slot.
- ③ Connect the 2 pin header to the system's LED light signal cable for frontal drive activity light.

ICY DOCK reserves the right to change product specifications, components, or accessories without prior notice. For the warranty information, please visit www.icydock.com/warranty.php

